



# Network Fingerprint Access Control & Time Attendance





<b>User Capacity</b> Fingerprint card PIN	<b>3000</b> 1000 1000 1000
<b>Operation Voltage</b>	+12V
<b>Access Mode</b>	Fingerprint, Card, PIN, Fingerprint& Card, Fingerprint & PIN
<b>Fingerprint Reader</b> Resolution Identification time FAR FRR	<b>Optical Fingerprint Module</b> 500 dpi < 1s <0.0001% <0.01%
<b>Proximity Card Reader</b> Radio Technology Read Range	<b>Industry Standard 16 bit</b> 125KHz Industry Proximity EM card 2~7 cm
<b>PIN Reader</b>	1~8 digits
<b>Wiring Connections</b>	Relay Output, Exit button, DOTL, Alarm, Wiegand output Wiegand Input, Door Bell
<b>Communication</b>	<b>USB, RS485, TCP/IP</b> USB for downloading/uploadding
<b>Relay</b> Adjustable Relay Output Time Lock Output Load Alarm Output Load	<b>One (NO, NC, Common)</b> 1~99 Second (5 seconds default) 2 Amp Maximum 5 Amp Maximum
<b>Wiegand Interface</b>	Weigand 26bit Input & Output
<b>Environment</b> Operating Temperature Operating Humidity	<b>Indoor</b> -20C ~ +50 C 20%RH - 90% RH
<b>Physical</b> Dimensions Unit Weight Shipping Weight	<b>ABS Enclosure</b> F5 - L140 X W105 X D35.5 (mm) 300g 500g

## User information Backup

Support downloading and uploading users' information by USB, users needn't be enrolled again if you need to install more devices.

